

# ZARA MOBILE ANTENNAS

- ☑ The ZARA27S, ZARA29S and ZARA40S are base loaded mobile antennas designed for aesthetics and flexibility.
- ☑ The whips can be mounted in an upright position regardless of the mounting angle of the base.
- ☑ Antennas supplied with 4 m RG-58 coaxial cable as standard, other lengths available on request.

Electrical Data	ZARA27S	ZARA29S
Frequency	27 MHz	29 MHz
Nominal Gain	Unity	Unity
Bandwidth VSWR <1,5:1	0.5 MHz	0.5 MHz
VSWR	< 1,5:1	< 1,5:1
Radiation Pattern	Omni-directional	Omni-directional
Polarisation	Vertical	Vertical
Rated Power	100 W	100 W
Impedance	50 Ω	50 Ω
Termination	4 m RG-58, no connector	4 m RG-58, no connector
Mechanical Data		
Max. wind velocity	220 km/h	220 km/h
Whip	Base loaded, 17 – 7PH SS	Base loaded, 17 – 7PH SS
Mounting Hole Size	19 mm	19 mm
Adjustment	180°	180°
Colour	Silver and Black	Silver and Black
Dims	1630 mm	1630 mm
Shipping Dims	0.4 kg / 156 x 11 x 5 cm	0.4 kg / 156 x 11 x 5 cm

## REPLACEMENT PARTS



**ZMC**  
A10AA0846A

Base & cable complete  
90° Mounting option



**SS10**  
A10AA0174A




**W27S**  
A10AA0336A  
**W29S**  
A10AA0234A  
**W40S**  
A10AA0337A

BASE LOADED  
WITH SPRING



**ZARA27S**  
A10AA0668A  
**ZARA29S**  
A10AA0669A



Horizontal Pattern