

7/16 F/F Coaxial RF Surge Protector, 100MHz - 512MHz, DC Block,
750W, IP67, .5uJ, 20kA, Filter, Bracket Down, Hole Mount



VHF50HD

Features

- Surge current of 20kA
- Max Power 750W
- Frequency range from 100 to 512 MHz VHF Band
- DIN-type Female connectors
- VSWR 1.1:1
- Waterproof IP67 rated
- DC Block
- Multi-strike capability
- CE & RoHS compliant

Applications

- Emergency response systems
- Public safety systems

Description

RF filter (also known as lightning arrester or surge arrester) VHF50HD from PolyPhaser, integrating a patented inductor designed for lightning surges and a RF blocking capacitor. This RF surge protector component is manufactured in a coaxial in-line design with wide operating frequency range. All PolyPhaser RF surge protector products are available in stock with same day shipping

Electrical Specifications

Surge Protector Type DC Handling		Surge Filter DC Block		
Description	Minimum	Typical	Maximum	Units
Frequency Range	100		512	MHz
Impedance		50		Ohms
VSWR			1.1:1	
Insertion Loss			0.1	dB
Input Power, CW			750	Watts
Surge Current IEC 61000-4-5 8/20μs waveform			20	kA
Throughput Energy for 3kA @ 8/20μs waveform			500	nJ

Mechanical Specifications

Size	
Length	4.21 in [106.93 mm]
Width/Diameter	3.01 in [76.45 mm]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications:
[7/16 F/F Coaxial RF Surge Protector, 100MHz - 512MHz, DC Block, 750W, IP67, .5uJ, 20kA, Filter, Bracket Down, Hole Mount VHF50HD](#)

7/16 F/F Coaxial RF Surge Protector, 100MHz - 512MHz, DC Block,
750W, IP67, .5uJ, 20kA, Filter, Bracket Down, Hole Mount



VHF50HD

Height	1.66 in [42.16 mm]
Weight	1.075 lbs [487.61 g]
Configuration	
Input Connector	7/16 DIN Female
Output Connector	7/16 DIN Female

Environmental Specifications

Temperature	
Operating Range	-50 to +85 deg C
Storage Range	-50 to +85 deg C
Ingress Protection (IP) Rating	IP67
Humidity	95%


Compliance Certifications

RoHS
CE

Plotted and Other Data

Notes:

Typical Performance Data




Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications:
[7/16 F/F Coaxial RF Surge Protector, 100MHz - 512MHz, DC Block, 750W, IP67, .5uJ, 20kA, Filter, Bracket Down, Hole Mount VHF50HD](#)

7/16 F/F Coaxial RF Surge Protector, 100MHz - 512MHz, DC Block,
750W, IP67, .5uJ, 20kA, Filter, Bracket Down, Hole Mount



VHF50HD



PolyPhaser protects and increases the reliability of global RF communications networks, including transportation, telecommunications, defense, security and industrial applications, with superior RF surge protection technologies including DC Block, DC Pass and Ultra Low PIM. Backed by responsive service and expert technical support PolyPhaser continually expands its product offering and services to serve engineers' urgent needs for RF components in mission critical communication networks.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: [7/16 F/F Coaxial RF Surge Protector, 100MHz - 512MHz, DC Block, 750W, IP67, .5uJ, 20kA, Filter, Bracket Down, Hole Mount VHF50HD](https://www.polyphaser.com/7-16-surge-protector-512mhz-filter-vhf50hd-p.aspx)

URL: <https://www.polyphaser.com/7-16-surge-protector-512mhz-filter-vhf50hd-p.aspx>

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. PolyPhaser reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. PolyPhaser does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and PolyPhaser does not assume any liability arising out of the use of any part or documentation.

VHF50HD CAD Drawing

